



Resistências / Resistors

Valores para a Série E

E series values

E6	E12	E24	E6	E12	E24
1.0	1.0	1.0	3.3	3.3	3.3
		1.1			3.6
	1.2	1.2		3.9	3.9
		1.3			4.3
1.5	1.5	1.5	4.7	4.7	4.7
		1.6			5.1
	1.8	1.8		5.6	5.6
		2.0			6.2
2.2	2.2	2.2	6.8	6.8	6.8
		2.4			7.5
	2.7	2.7		8.2	8.2
		3.0			9.1

E48	E96	E192	E48	E96	E192	E48	E96	E192	E48	E96	E192	E48	E96	E192
100	100	100	162	162	162	261	261	261	422	422	422	681	681	681
		101			164			264			427			690
	102	102		165	165		267	267		432	432		698	698
		104			167			271			437			706
105	105	105	169	169	169	274	274	274	442	442	442	715	715	715
		106			172			277			448			723
	107	107		174	174		280	280		453	453		732	732
		109			176			284			459			741
110	110	110	178	178	178	287	287	287	464	464	464	750	750	750
		111			180			291			470			759
	113	113		182	182		294	294		475	475		768	768
		114			184			298			481			777
115	115	115	187	187	187	301	301	301	487	487	487	787	787	787
		117			189			305			493			796
	118	118		191	191		309	309		499	499		806	806
		120			193			312			505			816
121	121	121	196	196	196	316	316	316	511	511	511	825	825	825
		123			198			320			517			835
	124	124		200	200		324	324		523	523		845	845
		126			203			328			530			856
127	127	127	205	205	205	332	332	332	536	536	536	866	866	866
		129			208			336			542			876
	130	130		210	210		340	340		549	549		887	887
		132			213			344			556			898
133	133	133	215	215	215	348	348	348	562	562	562	909	909	909
		135			218			352			569			920
	137	137		221	221		357	357		576	576		931	931
		138			223			361			583			942
140	140	140	226	226	226	365	365	365	590	590	590	953	953	953
		142			229			370			597			965
	143	143		232	232		374	374		604	604		976	976
		145			234			379			612			988
147	147	147	237	237	237	383	383	383	619	619	619			
		149			240			388			626			
	150	150		243	243		392	392		634	634			
		152			246			397			642			
154	154	154	249	249	249	402	402	402	649	649	649			
		156			252			407			657			
	158	158		255	255		412	412		665	665			
		160			258			417			673			